



SP6 Coaxial Surge Protectors

COAXIAL SURGE PROTECTORS

DC to 6 GHz Operation

The SP6 surge protectors offered by Laird are an integral part of any antenna installation involving the protection of sensitive equipment from surges caused by lightning. The ultra fast discharge design gives quick response to power surges and dumps the excess power safely to ground. Grounding is accomplished via a ground lug terminal or N bulkhead connector. The units have the ability to withstand multiple lightning strikes. The SP6 passes DC voltage so it is also suitable for those systems which pass DC power through the coax such as remote amplifiers. Construction is all plated brass to resist corrosion.

FEATURES

- Ultra fast gas discharge < 1KV / usec
- 0.2 dB @ 2.4 GHz,
.4 dB @ 5 GHz max insertion loss
- VSWR better than 1.4:1
- Rugged, lightweight and waterproof
- Bulkhead mount N female connector

APPLICATIONS

- Lightning protection for antenna systems
- 900 MHz, 2.4 GHz @ 5 GHz WLAN systems
- WiMAX

PARAMETER	MIN	TYP	MAX	UNITS
Frequency Range	DC	2400	6000	MHz
Insertion Loss	.1	.2	.4	dB
VSWR	1.1 : 1	1.2 : 1	1.4 : 1	
DC Breakdown Voltage		230		V
Impulse Breakdown Voltage (1 KV/uS MAX)		700		V
Impulse Wave Discharge (5 times)		10000		A
Impedance		50		OHM
Insulation Resistance (100 V)	50			
Imput Power			100	W
Operating Temperature	-40		+85	°C
Weight		4.5 (130)		oz (g)
Dimensions (incl connectors)	2.4 x 1.2 x 0.9 (60 x 31 x 23)			in (mm)

SYSTEM ORDERING

SP6-230-BFF DC to 6 GHz, bulkhead N female to N female, 230 V surge protector
SP6-230-BFM DC to 6 GHz, bulkhead N female to N male, 230 V surge protector

NOTES:

- All shipments F.O.B. Schaumburg, IL 60173

TE TECHNICAL SUPPORT CENTER

USA:	+1 (800) 522-6752
Canada:	+1 (905) 475-6222
Mexico:	+52 (0) 55-1106-0800
Latin/S. America:	+54 (0) 11-4733-2200
Germany:	+49 (0) 6251-133-1999
UK:	+44 (0) 800-267666
France:	+33 (0) 1-3420-8686
Netherlands:	+31 (0) 73-6246-999
China:	+86 (0) 400-820-6015

te.com

TE Connectivity, TE Connectivity (logo) and Every Connection Counts are trademarks. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

©2021 TE Connectivity. All Rights Reserved.

12/21 Original