



XAGA 1000

Pressurized Splice Closure System

- Underground splice used on pressurized and non-pressurized cable
- Re-enterable
- No cable bleed down required
- Use on aerial, buried or underground applications
- Simple and easy to install
- Provides excellent mechanical strength

The XAGA 1000 pressurized splice closure system provides a fast, simple way to seal telephone cable splices in pressurized or non-pressurized telephone cable. The XAGA 1000 splice closure is used for aerial, buried, and underground applications on polyethylene or lead sheathed cable in sizes up to 3600 pairs.

The XAGA 1000 splice closure sleeve is made of SuperSleeve sealing material which combines the strength and durability of composite design with proven heat-shrink technology. SuperSleeve sealing material is composed of several layers of specially blended polymers, adhesives and fiber-reinforcing layer. The fiber-reinforcing layer provides excellent mechanical strength and

eliminates the propagation of localized damage that can result from overheating or other errors in installation. Once the XAGA 1000 closure sleeve has been installed, the composite design of the SuperSleeve sealing material provides superior mechanical protection from forces such as impact, abrasion, UV light, and atmospheric contamination.

XAGA 1000 closure kits contain a number of components which are simple and easy to install. The wraparound sleeve design accommodates most cable sizes with just a few kit sizes, reducing inventories.

Selection Guide

Part Number	Product Descriptor	Sheath Opening	Minimum Cable Dia.	Maximum Splice Dia.	Approximate Cable Range (Pr)
765621	XAGA 1000 A2	21	0.6	2.4	50 - 200
189257	XAGA 1000 B2	21	1.2	3.6	200 - 400
249669	XAGA 1000 C2	21	1.5	4.8	300 - 600
456297	XAGA 1000 D2	24	2.2	6.2	900 - 1,200
495703	XAGA 1000 D4	37	2.2	6.2	900 - 2,100
327959	XAGA 1000 E2	24	2.6	7.8	1,200 - 2,400
475557	XAGA 1000 E3	31	2.6	7.8	1,200 - 3,600
468349	XAGA 1000 E4	37	2.6	7.8	1,200 - 3,600

Accessories


Standard Pack

734747	Branch off Clips A, B, C Kits	10 ea.
870747	Branch off Clips D, E Kits	10 ea.
719026	Adhesive Pad	50 ea.
996032	Heat Shield Pad 1' x 3'	1 ea.
337881	Heat Shield Pad 40" x 40"	1 ea.

Branch Off Clips



Heat Shield Pad



Adhesive Pad



Tyco Electronics Corporation
 8000 Purfoy Road
 Fuquay Varina, NC 27526-9349
 Tel: 919-557-8900
 Fax: 919-557-8498
 www.tycoelectronics.com
 www.telecomosp.com

SuperSleeve, XAGA, TE logo, and Tyco Electronics are trademarks.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, Tyco Electronics makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. Tyco Electronics' obligations shall only be as set forth in Tyco Electronics' Standard Terms and Conditions of Sale for this product and in no case will Tyco Electronics be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of Tyco Electronics products should make their own evaluation to determine the suitability of each such product for the specific application.