

PRODUCTS

Chilisin provides inductor turnkey solutions for EMI, power and RF and a global technical team to support its customers. Chilisin has become one of the few inductor suppliers capable of providing a complete "one-stop shopping" experience.



MHCI06030

Home > Products > Power Inductor > MHCI06030

- Power Inductor
- Chip Inductor
- Bead
- Common Mode Choke
- ◆ Product Search



Part Number : MHCI06030-1R5M-R8A

Structure	Closed Magnetic Circuit Type- Molding Processing & for Ultra High Current
Inductance(?H)	1.5
Tolerance(±%)	20
Test Frequency	100kHz,0.5V
RDC(?)Max	0.0121
Isat(A)Typ	14
Irms(A)Typ	10
Operating Temperature	- 5 5 °C ~ 1 2 5 °C(Including self - temperature rise)
L(mm)	6.6±0.2
W(mm)	7.3Max.
T(mm)	3Max.

- 1.Irms DC current (A) that will cause an approximate ?T of 40°C.
- 2.Isat DC current (A) that will cause Lo to drop approximately 30%

P/N	MHCI06030-1R5M-R8A
Part Numbering	
Dimensions	
Packing	
Recommended Pattern	
Electrical Characteristics Curve	

[Back](#)