

QO Load Centers – Main Breaker

Amps	Spaces	Max. Circuits	Cover	Catalog #	Ground Bar	UPC Code	Box Size
Indoor – QOM1 Main Breaker Frame Size							(see pg.18)
100	12	12	Combination	QO112M100C	PK9GTA	7-85901-84127-2	4
	12	20	Combination	QO11220M100C	PK15GTA	7-85901-84118-0	5
	16	16	Combination	QO116M100C	PK15GTA	7-85901-84775-5	5
	20	20	Combination	QO120M100C	PK15GTA	7-85901-84788-5	5
	24	24	Order Separately*	QO124M100*	PK15GTA	7-85901-84792-2	6
	32	32	Order Separately*	QO132M100	PK18GTA	7-85901-19337-1	6
125	24	24	Order Separately*	QO124M125*	PK15GTA	7-85901-84793-9	6
	32	32	Order Separately*	QO132M125	PK18GTA	7-85901-19338-8	6
Indoor – QOM2 Main Breaker Frame Size							(see pg.18)
150	24	24	Order Separately*	QO124M150*	PK15GTA	7-85901-84794-6	8
	30	30	Combination	QO130M150C	PK18GTA	7-85901-86743-2	8
	32	32	Order Separately*	QO132M150*	PK23GTA	7-85901-39489-1	9
200	20	40	Combination	QO12040M200C	PK23GTA	7-85901-84783-0	8
	24	24	Order Separately*	QO124M200*	PK15GTA	7-85901-84795-3	8
	30	30	Combination	QO130M200C	PK18GTA	7-85901-86754-8	8
	30	40	Combination	QO13040M200C	PK23GTA	7-85901-84800-4	8
	40	40	Combination	QO140M200C	PK23GTA	7-85901-86766-1	9
	42	42	Order Separately*	QO142M200*	PK23GTA	7-85901-39490-7	10
225	40	40	Order Separately*	QO140M225*	PK23GTA	7-85901-86767-8	10
Outdoor – QOM1 Main Breaker Frame Size							(see pg.19)
100	12	12	Rainproof	QO112M100RB*	PK9GTA	7-85901-86787-6	3R
	16	16	Rainproof	QO116M100RB*	PK12GTA	7-85901-86794-4	4R
	20	20	Rainproof	QO120M100RB	PK15GTA	7-85901-86798-2	4R
125	24	24	Rainproof	QO124M125RB*	PK15GTA	7-85901-86804-0	4R
Outdoor – QOM2 Main Breaker Frame Size							(see pg.19)
150	20	30	Rainproof	QO12030M150RB	PK18GTA	7-85901-86796-8	5R
	30	30	Rainproof	QO130M150RB*	PK18GTA	7-85901-86810-1	6R
200	20	40	Rainproof	QO12040M200RB	PK23GTA	7-85901-86797-5	5R
	30	30	Rainproof	QO130M200RB	PK18GTA	7-85901-86811-8	6R
	40	40	Rainproof	QO140M200RB	PK23GTA	7-85901-86813-2	7R
Outdoor – Feed Thru: 22,000 AIR (mobile home applications)							(see pg.19)
125	6	12	Rainproof	QO1612M125FTRB*▲	PK12GTA	7-85901-86816-3	3R
150	8	16	Rainproof	QO1816M150FTRB	PK15GTA-L	7-85901-86817-0	6R
200	8	16	Rainproof	QO1816M200FTRB	PK15GTA-L	7-85901-86818-7	6R



Main Circuit Breakers

- UL Listed, NOM Certified
- Single-Phase, 3-Wire
- 120/240 Vac—UL Listed
- 22,000 AIR*
- Convertible to Main Lugs or Lower Amperage Main Breaker
- Factory Installed Main Breaker
- Copper Bus
- Catalog Number Guide Page 17

Listings thru 200A mains meet Federal Specification W-P-115c as Type 1, Class 2.

* 22,000 AIR main circuit breaker UL listed for use ahead of QO and QOT 10,000 AIR branch breakers to permit their application systems with up to 22,000A available fault current.

* Contact Square D sales representative for ordering information.

▲ Item may require additional lead time.

▲ QO1612M125FTRB provided with QOM1 frame main circuit breaker.



QO120M100C



QO120M100RB



QO140M200C



QO140M200RB