

PRODUCTS

Chilisin provides inductor turnkey solutions for EMI, power and RF and a global technical team to support its customers. Chilisin has become one of the few inductor suppliers capable of providing a complete "one-stop shopping" experience.



SBK201209

Home > Products > Bead > SBK201209

- Power Inductor
- Chip Inductor
- Bead
- Common Mode Choke
- ◆ **Product Search**



Part Number : SBK201209T-102Y-N

Size Code(JIS/EIA)	2012/0805
Impedance ? (at 100MHz)	1000
Tolerance(±%)	25
Test Frequency	100 MHz,200 mV
RDC(?)Max	0.5
Rated Current(mA)Max	200
Operating Temperature	- 5 5℃~1 2 5℃(Including self - temperature rise)
L(mm)	2.00±0.20
W(mm)	1.25±0.20
T(mm)	0.90±0.20

1.Rate Current : Applied the current to coils the temperature rise shall not be more than 30℃

P/N	SBK201209T-102Y-N
Part Numbering	
Dimensions	
Packing	
Recommended Pattern	
Electrical Characteristics Curve	

[Back](#)