


Product availability: Stock - Normally stocked in distribution facility



Main

Product or component type	Extended I/O card
Range compatibility	Altivar 61Q Altivar Lift Altivar 71Q Altivar 71 Altivar 61
Supply	Internal supply for reference potentiometer, 10.5 V DC 10...11 V) , <0.01 A 1...10 kOhm overload and short-circuit protection Internal supply, 24 V DC 21...27 V) , <0.2 A overload and short-circuit protection
Analogue input number	2
Analogue input type	AI3-/AI3+ differential current programmable 0...20 mA 250 Ohm 4...6 ms 11 bits + sign AI4 software-configurable current 0...20 mA 250 Ohm 4...6 ms 11 bits AI4 software-configurable voltage 0...10 V DC, 24 V max 30000 Ohm 4...6 ms 11 bits
Analogue output number	2
Analogue output type	AO2 software-configurable current 0...20 mA 500 Ohm 4...6 ms 10 bits AO2 software-configurable voltage +/- 10 V DC 470 Ohm 4...6 ms 10 bits AO3 software-configurable current 0...20 mA 500 Ohm 4...6 ms 10 bits AO3 software-configurable voltage +/- 10 V DC 470 Ohm 4...6 ms 10 bits
Discrete output number	5
Discrete output type	LO3, LO4) assignable logic 4...6 ms level 1 PLC R4A, R4B, R4C) configurable relay logic
Discrete output logic	LO3, LO4) negative LO3, LO4) positive
Discrete input number	6
Discrete input type	RP) frequency control 4...6 ms LI11...LI14) programmable level 1 PLC 3.5 kOhm 4...6 ms
Discrete input logic	Negative LI11...LI14), >= 16 V, <= 10 V Positive LI11...LI14), <= 5 V, >= 11 V Positive RP), < 1.2 V, >= 3.5 V

Complementary

Electrical durability	100000 cycles configurable relay logic
Discrete output voltage	24 V DC <= 30 V) assignable logic
Maximum output current	0.2 A, assignable logic
Minimum switching current	3 mA 24 V DC configurable relay logic
Maximum switching current	Configurable relay logic 5 A 250 V AC resistive, cos phi = 1 Configurable relay logic 5 A 30 V DC resistive, cos phi = 1 Configurable relay logic 1.5 A 250 V AC inductive, cos phi = 0.4 7 ms Configurable relay logic 1.5 A 30 V DC inductive, cos phi = 0.4 7 ms
PTC probe input	TH2+, TH2- trip resistance 3 kOhm TH2+, TH2- reset resistance 1.8 Ohm TH2+, TH2- short circuit protection < 0.05 Ohm TH2+, TH2- for 6 PTC probe <= 1.5 Ohm
Discrete input voltage	24 V DC <= 30 V)programmable
Discrete input frequency	0...30 kHz frequency control

The information provided in this documentation contains general descriptions and/or technical characteristics of the products of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Electrical connection	Terminal, 1.5 mm ² / AWG 16, 2.21 lbf.in (0.25 N.m)
Net weight	0.66 lb(US) (0.3 kg)

Ordering and shipping details

Category	22135 - ATV61-71 ACCESSORIES
Discount Schedule	CP4C
GTIN	00785901807131
Package weight(Lbs)	0.40 kg (0.88 lb(US))
Returnability	Yes
Country of origin	ID

Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds which is known to the State of California to cause Carcinogen & Reproductive harm. For more information go to www.p65warnings.ca.gov
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration
Mercury free	Yes
RoHS exemption information	Yes
China RoHS Regulation	China RoHS Declaration

Contractual warranty

Warranty	18 months
----------	-----------