



RAYCHEM

TE Internal #: 532505-000


BNC Connector, Jack, 50 ohm, RG 142 / RG 400 / RG 58

Compatible With RF Cable Type, 1 Position, Wire & Cable, Panel

Mount, Solder, Straight, Brass

[View on TE.com >](#)

Connectors > RF Connectors > Coax Connectors



RF Interface: **BNC**

RF Connector Style: **Jack**

RF Connector Mated Outer Diameter (Approximate): **14.53 mm [ .572 in ]**

Impedance: **50 Ω**

Compatible With RF Cable Type: **RG 141, RG 142, RG 303, RG 400, RG 58**

**Features**

**Product Type Features**

RF Interface	BNC
RF Connector Style	Jack
Compatible With RF Cable Type	RG 141, RG 142, RG 303, RG 400, RG 58
Sealable	No
Connector & Contact Terminates To	Wire & Cable

**Configuration Features**

Number of Positions	1
---------------------	---

**Electrical Characteristics**

Impedance	50 Ω
-----------	------

**Body Features**

Body Material	Brass
Body Plating Material	Nickel

**Contact Features**

RF Connector Center Contact Underplating Material	Nickel
RF Connector Center Contact Plating Material	Gold (Au)
RF Connector Center Contact Material	Beryllium Copper

**Termination Features**

Termination Method to Wire & Cable	Solder
------------------------------------	--------



### Mechanical Attachment

Panel Mount Feature Type	Hex Nut
Connector Mounting Type	Panel Mount

### Housing Features

Body Orientation	Straight
------------------	----------

### Dimensions

Panel Thickness (Recommended)	3.2 mm[.126 in]
RF Connector Mated Outer Diameter (Approximate)	14.53 mm[.572 in]

### Packaging Features

Packaging Method	Box
------------------	-----

### Other

Coupling Nut Base Material	Brass
Grade	Military
Dielectric Material	Polytetrafluoroethylene (PTFE)

### Product Compliance

[For compliance documentation, visit the product page on TE.com>](#)

EU RoHS Directive 2011/65/EU	Not Compliant
EU ELV Directive 2000/53/EC	Not Compliant
China RoHS 2 Directive MIIT Order No 32, 2016	有害物质含量超出标准 Restricted Substance(s) Above Threshold
EU REACH Regulation (EC) No. 1907/2006	Current ECHA Candidate List: JUNE 2025 (250) Candidate List Declared Against: JUNE 2025 (250) SVHC > Threshold: Pb (37% in Solder) <b>Article Safe Usage Statements:</b> Do not eat, drink or smoke when using this product. Wash thoroughly after handling. Recycle if possible and dispose of the article by following all applicable governmental regulations relevant to your geographic location.
Halogen Content	Low Bromine/Chlorine - Br and Cl < 900 ppm per homogenous material. Also BFR /CFR/PVC Free
Solder Process Capability	Not applicable for solder process capability

#### Product Compliance Disclaimer

This information is provided based on reasonable inquiry of our suppliers and represents our current actual knowledge based on the information they provided. This information is subject to change. The part numbers that TE has identified as


EU RoHS compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, mercury, PBB, PBDE, DBP, BBP, DEHP, DIBP, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2011/65/EU (RoHS2). Finished electrical and electronic equipment products will be CE marked as required by Directive 2011/65/EU. Components may not be CE marked. Additionally, the part numbers that TE has identified as EU ELV compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, and mercury, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2000/53/EC (ELV). Regarding the REACH Regulation, the information TE provides on SVHC in articles for this part number is based on the latest European Chemicals Agency (ECHA) 'Guidance on requirements for substances in articles' posted at this URL: <https://echa.europa.eu/guidance-documents/guidance-on-reach>

## Compatible Parts



TE Part # EG8162-000  
HL1920E-230V-EURO

## Customers Also Bought



TE Part #814344-000  
202D121-25-0

## Documents

### Product Drawings

[RBD-50-M-02](#)

English

### CAD Files

Customer View Model

[ENG\\_CVM\\_CVM\\_532505-000\\_O.2d\\_dxf.zip](#)

English

### 3D PDF

3D

Customer View Model

[ENG\\_CVM\\_CVM\\_532505-000\\_O.3d\\_igs.zip](#)

English

Customer View Model

[ENG\\_CVM\\_CVM\\_532505-000\\_O.3d\\_stp.zip](#)



English

By downloading the CAD file I accept and agree to the [Terms and Conditions](#) of use.

---

### Datasheets & Catalog Pages

[1654025\\_Sec8\\_BNC\\_TNC](#)

English

[Harness Repair Products Quick Reference Guide](#)

English

---

### Product Specifications

[Installation Procedure for RF-One Step BNC and TNC Connector](#)

English